

GRENTON RELAYX2 REL-019-T-01

RELAY OUTPUT MODULE FOR DIN RAIL ASSEMBLY



The relay output module allows you to control any electrical device without the need to use additional control relays.

- two relay outputs
- enables you to connect a direct load up to 3.6 kVA
- enables the following functions: switching, continuous activation and specific-time activation
- signals output state with a diode



CONFIGURATION PARAMETERS

CHARACTERISTICS

Name	Description	
Value	Returns 1 for output set at "On" and 0 for output set at "Off"	
StatisticState	Measurement type. Off - turned off; Continuous - Load measurement throughout the machine cycle/Load measurement over the entire life cycle of the device	
Load	Multiplier of measured value. For StatisticState: Continous - consumption value per unit time;	

METHODS

Name	Description
SetValue	SetValue Sets output value to 1 or 0
Switch	Changes the output value from 0 to 1 or from 1 to 0. The first parameter is the time of change: - 0 – switches output to continuous mode - num – switches output for a time specified by a parameter (in milliseconds)
SwitchOn	Sets output value to 1
SwitchOff	Sets output value to 0

EVENTS

Name	Description	
OnChange	Occurs when a change in the state takes place (regardless of the value)	
OnSwitchOn	Occurs when "On" is set at output	
OnSwitchOff	Occurs when "Off" is set at output	

TECHNICAL SPECIFICATIONS

DC supply	5 V
average current input	4.18 mA
max. current input	112 mA
contact arrangement	2x NO
weight	82 g
dimensions (H/W/D)	58/36/90 mm
max. connection wire section	≤ 2.5 mm ²
size [DIN]	2
operating temperature range	0 to +40°C
maximum load	3,600 VA per channel



WIRING DIAGRAM

